

Osram


Converter OTe 10-13-25-35

Leistung in Watt

- 10
- 13
- 25
- 35



Technical details

País de origen	 Alemania
Fabricante	Osram
Atenuación	dimnable con control de fase inversa y con reguladores de control de fase
vida en horas	50.000
Índice de protección / Protección IP	IP20

Descripción

The Osram converter OTe 10-13-25-35 is suitable for LED lamps. This converter with its compact housing can only be used for indoor applications. The converter can be dimmed on site with an optional trailing or leading edge phase dimmer. The converter is suitable for the following powers in watts:

- OTe 10: suitable for 5-10 Watt
- OTe 13: suitable for 10-13 Watt
- OTe 25: suitable for 13-25 Watt
- OTe 35: suitable for 19-35 Watt